



Light Source	CREE XP-G2
Light Output	80 lumens
Running Time	14 hours
Battery	3 x AAA Alkaline
Product Dimensions	70 x 60 x 60 mm
Product Weight	110 g (excluding batteries)
NS Part No	NSEXHT80
Supplied with	Headtorch, headstrap, Hex key
CERTIFICATIONS	SUITABLE FOR USE in ZONE 0 area
UL	Class I Div 1&2 Grp ABCD Class II Div 1&2 Grp EFG Class III / Temperature Code T4 IP67 File number E324236 Gas: II 1G Ex ia IIC T4 Ga Mine: I M1 Ex ia I Ma DEMKO 15 ATEX 1546X Gas: Ex ia IIC T4 Ga Mine: Ex ia I Ma IECEx UL 15.0086X
ATEX	
IECEx	
REACH	Approved
RoHS	Approved
CE	Approved 0518



Mode operation - Product information - Warning

Operation

- Rotate the headlight clockwise to turn on the light and anti-clockwise to switch the light off.

Battery Installation

- Unscrew the cover retaining screw and remove the cover to reveal the battery compartment.
- Insert 3 x AAA batterie. Fill new batteries according to the (+) positive and (-) negative marks inside the battery compartment.
- Then replace the cover in line with the screw. Then lock in position by tightening the screw.

Battery Replacement - USE ONLY BATTERY TYPE BELOW // ALKALINE TYPE

PREFERRED BATTERIES RECOMMENDED BY NIGHTSEARCHER

- Energizer® Lithium AA/AAA batteries

ALTERNATIVE BATTERIES RECOMMENDED

- Energizer® E92
- Duracell® MN2400
- Panasonic® AAA LR03
- Rayovac® AAA LR03

Warning - REPLACE BATTERIES ONLY IN NON HAZARDOUS AREAS

- The screw shall be secured tightly after opening and closing of the enclosure
- Do not flash the light beam directly to people's eyes

General Warning

- Do not open the light in hazardous locations
- Replace batteries only in non-hazardous areas
- Do not mix new batteries with used batteries or mix batteries from different battery manufacturer or from different type
- Remove the batteries when unused for a period of time to prevent battery leakage in the device
- Substitution of components may impair intrinsic safety



Utilisation - Information produit - Avertissement

Opération

- Tournez le phare dans le sens horaire pour allumer la lumière et anti-horaire pour éteindre la lumière.

Installation des batteries

- Dévisser la vis de fixation du couvercle et retirez le couvercle pour ouvrir le compartiment à batteries.
- Insérer 3 x batteries alcalines AAA, Insérer les piles neuves selon les bornes (+) positives et (-) négatives à l'intérieur du compartiment à batterie.
- Remplacer le couvercle en ligne avec les vis. Puis verrouiller les positions en serrant les x4 vis de sécurité.

Remplacement de la batterie - UTILISATION SEULEMENT TYPE DE PILE CI-DESSOUS // TYPE ALCALINE

BATTERIES DE REMPLACEMENT RECOMMANDÉES PAR NIGHTSEARCHER

- Energizer® E92
- Duracell® MN2400
- Panasonic® AAA LR03
- Rayovac® AAA LR03

Attention - REMPLACER LES BATTERIES UNIQUEMENT DANS DES ZONES NON DANGEREUSES

- La vis doit être fixée hermétiquement après ouverture et fermeture de la torche
- Ne pas illuminer le faisceau lumineux directement vers les yeux

Précautions

- Ne pas ouvrir la torche dans des zones dangereuses.
- Remplacez les batteries uniquement dans des zones non dangereuses
- Ne pas mélanger des piles neuves avec des piles usagées ou mélanger des piles de fabricant de batterie différent ou de type différent.
- Retirez les piles lorsque la torche n'est pas inutilisée pendant une période de temps supérieur à 10 jours pour empêcher toute fuite de la batterie dans l'appareil.
- La substitution de composants peut compromettre la sécurité intrinsèque de la torche.

GUARANTEE TERMS

NightSearcher products have been carefully tested and inspected before shipment and are guaranteed to be free from defective materials and workmanship for a period of 12 months (battery not covered) from the date of purchase, provided that the enclosed instructions have been followed. Should you experience problems with your NightSearcher product, please return the item, complete with any chargers, to your place of purchase or contact NightSearcher Ltd direct. Your NightSearcher guarantee does not apply to consumables (LEDs and battery), normal wear and tear, nor does it cover any damage caused by misuse, careless or unsafe handling, alterations, accidents or repairs attempted or made by any personnel without prior approval from NightSearcher Ltd. Your NightSearcher guarantee is not effective unless you can provide a dated proof of purchase. Please note that this guarantee does not affect your statutory rights. If at any time, you need to dispose of this product or parts of this product: Please note that waste electrical products, batteries and bulbs should not be disposed of with household waste. Please recycle where facilities exist, check with your local authority for recycling advice.

NIGHTSEARCHER LIMITED - Unit 4 Applied House - Fitzherbert Spur - Farlington - Portsmouth - PO6 1TT - UNITED-KINGDOM

Visit our website on www.nightsearcher.com